


Signal LED Emergency Downlight

Supplied c/w Remote Driver and Battery Pack



- Economic and compact LED Non-Maintained fixed downlight
- White powder coat paint finish
- LED combines power and green charge indicator
- 3 hour emergency output
- 120° beam angle



- * 1 lux minimum must be used for all marked emergency escape routes, to be measured down the centre line of the escape route itself
- ** 0.5 lux minimum must be used for areas larger than 60m², the maximum value is to be measured across the area excluding 0.5 metre border around the edge of the room
- *** Explanation of the symbols:-
Transverse - Wall
 Distance to wall from side of fitting
Transverse - Transverse
 Side to side spacing
Axial - Wall
 Distance to wall from end of fitting
Axial - Axial
 End to end spacing

***	Escape route 2 metres wide (1 Lux minimum) *			
	Transverse to Wall	Transverse to Transverse	Axial to Wall	Axial to Axial
Mounting Height (M)	3.3	6.5	3.3	6.5
2.5	3.3	6.5	3.3	6.5
4	3.1	8.3	3.1	8.3
6	-	-	-	-

***	Open (Anti-Panic) area (0.5 Lux Minimum) **			
	Transverse to Wall	Transverse to Transverse	Axial to Wall	Axial to Axial
Mounting Height (M)	3.1	6.7	3.1	6.7
2.5	3.1	6.7	3.1	6.7
4	3.4	8.6	3.4	8.6
6	3	9	3	9

LED Information

Total (Watts)	1.5W
Lumens Delivered	
Emergency Mode	124lm
Beam Angle	120°
CCT	6500K
Input	230V
Hertz	50/60Hz
Operating Temp	0°C to 45°C

Code	Lamp	Description
ASLED/3NM	LED	1.5W Non-Maintained

Accessory	ASBP/8	3.6V 2Ah Ni-Cd Replacement Battery
------------------	---------------	------------------------------------

