



collingwood

01604 495 151
collingwoodlighting.com

- collingwoodled
- /collingwoodlighting
- collingwoodlighting

Daylight Sensor

Daylight harvesting sensor with photocell

Features

IP rating	IP65
Dimmable Option	Yes (0-10V and PWM)
Input	10.5-15V DC

Installation information

Install Connector Type	Zhaga Book 18
Weight	0.03
Maximum ambient temperature	-20 to +60

Accessories

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------

PRODUCT CODES

Product code	Finish	Description
HBDS	Matt black RAL9017	Daylight harvesting sensor with photocell

Guarantee

5 years

Features & benefits

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Daylight harvesting
Default is
Options -
30Lux/50Lux/80Lux/120Lux
200Lux/250Lux/300Lux/350Lux
400Lux

When ambient brightness is lower than the preset lux level options, the luminaire dim up to maintain the desired lux level, when ambient brightness is brighter than preset lux level, the luminaire will hold off.

Alternately, press 'Scene' button on remote to Instead of giving a specific lux level

Photocell Lights will switch automatically ON when ambient brightness is lower than preset level and automatically OFF when ambient brightness is 10 times higher than preset level.

Daylight photocell
Default is
Options to have 2Lux/10Lux