



PIR Sensor

Passive infra-red motion sensor with daylight threshold switch

Features

IP rating	IP65
Dimmable Option	Yes (0-10V and PWM)
Input	10.5-15V DC

Installation information

Install Connector Type	Zhaga Book 18
Weight	0.03
Maximum ambient temperature	-20 to +60

Accessories

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------

PRODUCT CODES

Product code	Finish	Description
HBPIR	Matt black RAL9017	Passive infra-red (PIR) motion sensor with daylight threshold switch



collingwood

01604 495 151
collingwoodlighting.com

- collingwoodled
- /collingwoodlighting
- collingwoodlighting

Guarantee

5 years

Features & benefits

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Typical installation height 8-13m

Hold time
Default is 5 seconds
Options -
30s/1min/3min/5min/10min/20min/30min

Stand-by dimming level
Default is 10%
Options - 20%/30%/50%

Stand-by period
Default is 0 seconds
Options -
10s/30s/1min/5min/10min/30min

Daylight threshold
Default is 'disable'
Options -
2Lux/10Lux/30Lux/50lux
120Lux/200Lux/250Lux
300Lux/350Lux/400Lux