



Technical Specification

Product Code: VPPN019WH

Description: 10AX 4 Gang 2 Way Plate Switch



General Information

| Plate Design & Finish Victorian Pearl Nickel Insert & Gasket Colour White Materials Front Plate: Stainless Steel Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass Terminal Screws: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel Gasket: Nylon Maximum Voltage 250V~ 50Hz Load Rating 10AX (Suitable for Inductive Loads) Plate Fixing Centres 120.6mm Terminal Size 3.5mmø Terminal Torque 0.5Nm Terminal Stread t | Dimensions | 146mm (W) x 88mm (H) x 8mm (D) |
|--|-------------------------|--|
| Insert & Gasket Colour White Materials Front Plate: Stainless Steel Insert & Rocker Switch: Urea Rear Housing: Nylon Terminal: Brass Terminal: Screws: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel Gasket: Nylon Maximum Voltage 250V~ 50Hz Load Rating 10AX (Suitable for Inductive Loads) Plate Fixing Centres 120.6mm Terminal Screw 3.5mma Terminal Capacity 4× 1.5mm² or 2 x 2.5mm² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to ± 40°C Warranty 10 Years Standards BS EN 60669-1:1999 ± A1:2002 ± A2:2008 | Dimensions With Gasket | 149mm (W) x 91mm (H) x 9mm (D) |
| Materials Front Plate: Stainless Steel Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass Terminals: Brass Terminals: Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel Gasket: Nylon Maximum Voltage 250V~50Hz Load Rating 10AX (Suitable for Inductive Loads) Plate Fixing Centres 120.6mm Terminal Torque 0.5Nm Terminal Scapacity 4 x 1.5mm ² or 2 x 2.5mm ² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sle | Plate Design & Finish | Victorian Pearl Nickel |
| Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass Terminal Screws: Steel & Yellow Passivated Contacts: Silver 'on-lay' Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel Gasket: Nylon Maximum Voltage 250V – 50Hz Load Rating 10AX (Suitable for Inductive Loads) Plate Fixing Centres 120.6mm Terminal Size 3.5mmø Terminal Torque 0.5Nm Terminal Capacity 4 x 1.5mm° or 2 x 2.5mm° Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Terminant Torque -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Insert & Gasket Colour | White |
| Load Rating 10AX (Suitable for Inductive Loads) Plate Fixing Centres 120.6mm Terminal Size 3.5mmø Terminal Torque 0.5Nm Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal diagram with the relevant product. | Materials | Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass Terminal Screws: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel |
| Plate Fixing Centres 120.6mm Terminal Size 3.5mmø Terminal Torque 0.5Nm Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 | Maximum Voltage | 250V~ 50Hz |
| Terminal Size 3.5mmø Terminal Torque 0.5Nm Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 | Load Rating | 10AX (Suitable for Inductive Loads) |
| Terminal Torque 0.5Nm Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Plate Fixing Centres | 120.6mm |
| Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm² Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Terminal Size | 3.5mmø |
| Two Way Yes Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Terminal Torque | 0.5Nm |
| Ingress Protection IP20 Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Terminal Capacity | 4 x 1.5mm ² or 2 x 2.5mm ² |
| Back Box Depth 16mm Minimum Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Two Way | Yes |
| Termination Type Screw Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Ingress Protection | IP20 |
| Operational Temperature -5°C to +40°C Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Back Box Depth | 16mm Minimum |
| Warranty 10 Years Standards BS EN 60669-1:1999 +A1:2002 +A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Termination Type | Screw |
| Standards BS EN 60669-1:1999 + A1:2002 + A2:2008 Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Operational Temperature | -5°C to +40°C |
| Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Warranty | 10 Years |
| diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal | Standards | BS EN 60669-1:1999 +A1:2002 +A2:2008 |
| interonal goable with house of the withhand hange. | Additional Information | |