



## **Technical Specification**

Product Code: VPSS012BK

## Description: 10AX 2 Gang 2 Way Plate Switch





## **General Information**

Dimensions   88mm (W) × 88mm (H) × 8mm (D)     Dimensions With Gasket   91mm (W) × 91mm (H) × 9mm (D)     Plate Design & Finish   Victorian Stainless Steel     Insert & Gasket Colour   Black     Materials   Front Plate: Stainless Steel     Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass   Rear Housing: Nylon Terminals: Brass     Terminal Screws: Steel & Yellow Passivated Contacts: Silver 'on-lay' Copper / Brass Internal Busbars: Formed Pressed Brass     Earth Strap: Mild Steel Gasket: Nylon     Maximum Voltage   250V~ 50Hz     Load Rating   10AX (Suitable for Inductive Loads)     Plate Fixing Centres   60.3mm     Terminal Capacity   4 x 1.5mm² or 2 x 2.5mm²     Two Way   Yes     Ingress Protection   IP20     Back Box Depth   16mm Minimum     Termination Type   Screw     Operational Temperature   -5°C to +40°C     Warranty   10 Years     Standards   BS EN 60669-1:1999 +A1:2002 +A2:2008     Additional Information   Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving a		
Plate Design & Finish Victorian Stainless Steel   Insert & Gasket Colour Black   Materials Front Plate: Stainless Steel   Insert & Rocker Switch: Urea   Rear Housing: Nylon   Terminals: Brass   Terminal: Brass   Terminal Screws: Steel & Yellow Passivated   Contacts: Silver "on-lay" Copper / Brass   Internal Busbars: Formed Pressed Brass   Earth Stray: Mild Steel   Gasket: Nylon   Maximum Voltage 250V 50Hz   Load Rating 10AX (Suitable for Inductive Loads)   Plate Fixing Centres 60.3mm   Terminal Stee 3.5mme   Terminal Capacity 4 x 1.5mm <sup>2</sup> or 2 x 2.5mm <sup>2</sup> Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.   Bare earth cables must always be covered with app	Dimensions	88mm (W) x 88mm (H) x 8mm (D)
Insert & Gasket Colour Black   Materials Front Plate: Stainless Steel   Insert & Rocker Switch: Urea Rear Housing: Nylon   Terminals: Brass Terminals: Brass   Terminal Screws: Steel & Yellow Passivated Contracts: Silver "on-lay" Copper / Brass   Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel   Gasket: Nylon Gasket: Nylon   Maximum Voltage 250V~ 50Hz   Load Rating 10AX (Suitable for Inductive Loads)   Plate Fixing Centres 60.3mm   Terminal Stee 3.5mmo   Terminal Capacity 4 x 1.5mm <sup>2</sup> or 2 x 2.5mm <sup>2</sup> Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to + 40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 + A1:2002 + A2:2008	Dimensions With Gasket	91mm (W) x 91mm (H) x 9mm (D)
Materials Front Plate: Stainless Steel   Insert & Rocker Switch: Urea Rear Housing: Nylon   Terminals: Brass Terminals: Brass   Terminals: Brass Terminals: Brass   Terminal: Strass: Terminal: Strass   Terminal: Strass: Terminal: Strass   Terminal: Strass: Terminal: Strass   Terminal: Strap: Mild Steel Gasket: Nylon   Maximum Voltage 250V~ 50Hz   Load Rating 10AX (Suitable for Inductive Loads)   Plate Fixing Centres 60.3mm   Terminal Size 3.5mmø   Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm²   Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Terminalton Type Screw   Operational Temperature -5°C to ±40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 ±A1:2002 ±A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.   Bare earth Cables must always be covered with appropriate sleeving and wired to the earth terminal.	Plate Design & Finish	Victorian Stainless Steel
Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass Terminal: Strews: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Earth Strap: Mild Steel Gasket: NylonMaximum Voltage Earth Strap: Mild Steel Gasket: NylonComment Pressed Brass Earth Strap: Mild Steel Gasket: NylonMaximum Voltage Load Rating20V~ 50HzLoad Rating10AX (Suitable for Inductive Loads)Plate Fixing Centres Terminal Size Terminal Torque0.5NmTerminal Torque Terminal Capacity4 x 1.5mm² or 2 x 2.5mm²Two Way YesYesIngress Protection Back Box Depth16mm MinimumTermination Type WarrantyScrewOperational Temperature Warranty5°C to +40°C U YearsStandardsBS EN 60669-1:1999 +A1:2002 +A2:2008Additional Information Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal. 	Insert & Gasket Colour	Black
Load Rating10AX (Suitable for Inductive Loads)Plate Fixing Centres60.3mmTerminal Size3.5mmøTerminal Torque0.5NmTerminal Capacity4 x 1.5mm² or 2 x 2.5mm²Two WayYesIngress ProtectionIP20Back Box Depth16mm MinimumTermination TypeScrewOperational Temperature-5°C to +40°CWarranty10 YearsStandardsBS EN 60669-1:1999 +A1:2002 +A2:2008Additional InformationEnsure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Materials	Insert & Rocker Switch: Urea Rear Housing: Nylon Terminals: Brass Terminal Screws: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel
Plate Fixing Centres 60.3mm   Terminal Size 3.5mmø   Terminal Torque 0.5Nm   Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm²   Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008	Maximum Voltage	250V~ 50Hz
Terminal Size 3.5mmø   Terminal Torque 0.5Nm   Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm²   Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008	Load Rating	10AX (Suitable for Inductive Loads)
Terminal Torque 0.5Nm   Terminal Capacity 4 x 1.5mm² or 2 x 2.5mm²   Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Plate Fixing Centres	60.3mm
Terminal Capacity4 x 1.5mm² or 2 x 2.5mm²Two WayYesIngress ProtectionIP20Back Box Depth16mm MinimumTermination TypeScrewOperational Temperature-5°C to +40°CWarranty10 YearsStandardsBS EN 60669-1:1999 +A1:2002 +A2:2008Additional InformationEnsure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Terminal Size	3.5mmø
Two Way Yes   Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Terminal Torque	0.5Nm
Ingress Protection IP20   Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Terminal Capacity	4 x 1.5mm <sup>2</sup> or 2 x 2.5mm <sup>2</sup>
Back Box Depth 16mm Minimum   Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Two Way	Yes
Termination Type Screw   Operational Temperature -5°C to +40°C   Warranty 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Ingress Protection	IP20
Operational Temperature Warranty -5°C to +40°C 10 Years   Standards BS EN 60669-1:1999 +A1:2002 +A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Back Box Depth	16mm Minimum
Warranty 10 Years   Standards BS EN 60669-1:1999 + A1:2002 + A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Termination Type	Screw
Standards BS EN 60669-1:1999 + A1:2002 + A2:2008   Additional Information Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Operational Temperature	-5°C to +40°C
<b>Additional Information</b> Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Warranty	10 Years
diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.	Standards	BS EN 60669-1:1999 +A1:2002 +A2:2008
	Additional Information	diagram with the relevant product. Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.