info@gaplighting.co.uk

**TECHNICAL DATA** 

**CONTROL & POWER** 

PRODUCT CODE

T-CON5



## WARRANTY

3 years guarantee

@GAPLightingLtd

GAP Lighting Ltd

/GAPLightingLtd


GAP Lighting Ltd





#### PRODUCT DESCRIPTION

A smart 5 in 1 RF controller which enables wireless connection to Smart Sync products. It can be easily controlled witha choice of touch remotes, the GAP Light App or any third party Apps and voice control systems.



# **PRODUCT FEATURES**

12v or 24v constant voltage LED controller

Terminal screw connections / jack input

For use with 12v/24vDC LED luminaires

Indicator light to show output mode

Mode switch to change output mode

For indoor use or within an enclosure for outdoor use

PC housing

Mounting tabs for securing to a flat surface

Wire direct to LED for dimming and colour changing LED

Suitable for interior and exterior architectural, domestic, retail and commercial applications.













Choose your preferred remote:

T-8Z-REMOTE / T-RGB-CCT / T-4Z-REMOTE / T-8Z-WALL / T-4Z-WALL-B / T-4Z-WALL

T-4WIFI for use with the GAP Light App



#### PRODUCT DATA

Model	T-CON5
Control	Single Colour   RGB   RGBW   CCT   RGB-CCT
Frequency	2.4 GHz high frequency wireless   WIFI Control
Output Current	15A max   6A / channel
Input	12v / 24v constant voltage
Working Temp.	-20° to +60°
Protection	IP20
Dimensions	L 125mm   W 37mm   D 22mm
Remote Distance	Up to 30m range
Connection	Common anode
Weight	60g
Approvals	CE   ROHS

# PRODUCT COMPATIBILITY

iPanel / Solas / App Lamps / Echo / iBar / iFlood / Eco SPot / Celeste / iFlex / Flex CCT / Flex RGBW / Flex 20 / Flex 65 / Aquaflex / Module / SS316 RGB/W / GL-RGBW / Marina RGB / Pod RGB / Ledstar RGB / Blade / FL-RGB / FL-RGBW / Linear RGB/W / Spectrum

## **INSTALLATION**

Please follow installation guide